

NAME

fbdev - video driver for framebuffer device

SYNOPSIS

Section Device

Identifier *devname*

Driver fbdev

BusID pci:bus:dev:func

...

EndSection

DESCRIPTION

fbdev is an Xorg driver for framebuffer devices. This is a non-accelerated driver, the following framebuffer depths are supported: 8, 15, 16, 24. All visual types are supported for depth 8, and TrueColor visual is supported for the other depths. Multi-head configurations are supported.

SUPPORTED HARDWARE

The **fbdev** driver supports all hardware where a framebuffer driver is available. fbdev uses the os-specific submodule [fbdevhw\(4\)](#) to talk to the kernel device driver. Currently a fbdevhw module is available for linux.

CONFIGURATION DETAILS

Please refer to [xorg.conf\(5\)](#) for general configuration details. This section only covers configuration details specific to this driver.

For this driver it is not required to specify modes in the screen section of the config file. The **fbdev** driver can pick up the currently used video mode from the framebuffer driver and will use it if there are no video modes configured.

For PCI boards you might have to add a BusID line to the Device section. See above for a sample line.

The following driver **Options** are supported:

Option fbdev *string*

The framebuffer device to use. Default: /dev/fb0.

Option ShadowFB *boolean*

Enable or disable use of the shadow framebuffer layer. Default: on.

Option Rotate *string*

Enable rotation of the display. The supported values are CW (clockwise, 90 degrees), UD (upside down, 180 degrees) and CCW (counter clockwise, 270 degrees). Implies use of the shadow framebuffer layer. Default: off.

SEE ALSO

[Xorg\(1\)](#), [xorg.conf\(5\)](#), [Xserver\(1\)](#), [X\(7\)](#), [fbdevhw\(4\)](#)

AUTHORS

Authors include: Gerd Knorr, Michel Dnzer, Geert Uytterhoeven