

NAME

halt, poweroff, reboot - Halt, power-off or reboot the machine

SYNOPSIS

halt [OPTIONS...]

poweroff [OPTIONS...]

reboot [OPTIONS...]

DESCRIPTION

halt, poweroff, reboot may be used to halt, power-off or reboot the machine.

OPTIONS

The following options are understood:

--help

Print a short help text and exit.

--halt

Halt the machine, regardless of which one of the three commands is invoked.

-p, --poweroff

Power-off the machine, regardless of which one of the three commands is invoked.

--reboot

Reboot the machine, regardless of which one of the three commands is invoked.

-f, --force

Force immediate halt, power-off, reboot. Do not contact the init system.

-w, --wtmp-only

Only write wtmp shutdown entry, do not actually halt, power-off, reboot.

-d, --no-wtmp

Do not write wtmp shutdown entry.

--no-wall

Do not send wall message before halt, power-off, reboot.

EXIT STATUS

On success, 0 is returned, a non-zero failure code otherwise.

NOTES

These are legacy commands available for compatibility only.

SEE ALSO

[systemd\(1\)](#), [systemctl\(1\)](#), [shutdown\(8\)](#), [wall\(1\)](#)